

MT-58 5 GHz Digital Transmitter

Features

- The MT-58 is a digital transmitter with a rotatable 3.5 mm phone jack for easy fitting to a musical instrument, PC or projector with a built-in pickup.
- The compact MT-58 can be snugly attached to the instruments with various instrument holders and is easy to install and remove. It can pair with an MR-58 digital pedal receiver to get rid of the problem of tangled cables for carefree performances with truly wireless transmission.
- Operates in ISM 5 GHz frequency band and eliminates the interference from 2.4 GHz telecommunication products as well as the UHF band, which has more and more severe interference and strict telecom regulations, thus the MT-58 has excellent performance especially for instrument signals. Its digital circuitry design eliminates the distortion caused by the analog system, so the natural sound of the musical instruments can be reproduced.



Specifications

| | |
|------------------|---|
| Frequency Band | ISM 5.8 GHz |
| RF Power Output | 20 mW (country dependent) |
| Max. Audio Input | 6.5 dBV |
| Battery Meter | 4-level green/red LED display |
| Impedance | Approx. 1 M Ω |
| Connector | 3.5 mm. Another 3.5 mm to 6.3 mm threaded adapter is included. |
| Battery | One 18500 Li-ion battery |
| Dimensions | 35 × 84 × 29 mm (W × H × D) |
| Weight | Approx. 61 g |
| Accessory | MP-24 charger |
| Note | Refer to the actual product in the event of product description discrepancy |